

SB4000A DATA SHEET

2.92mm Bias Tee From 0.03 MHz to 40 GHz Rated To 500 mA And 25 Volts DC

Fairview Microwave's SB4000A is a 2.92mm bias tee (also known as bias T) that operates from 30 kHz to 40 GHz with a bias rating of 500 mA and 25 VDC. This bias tee is configured with 2.92mm inputs on the RF ports and solder pin on the bias port. SB4000A 2.92mm bias T offers good electrical performance featuring 4.75 dB max insertion loss and 40 dB min isolation.

Bias tees are typically used to inject a DC signal into an RF path such as when biasing an amplifier or any other active device, supplying power to the connected output without disrupting the RF signal. They can also be used as DC returns to provide a ground return path for the input device or DC blocks to prevent direct current signals from flowing through the output device. Fairview Microwave's bias tees are available in various connector configurations over different frequency bands to fit your needs, all of which ship the same day.

Electrical Specifications

Description	Min	Тур	Мах	Units
Frequency Range	30KHz		40	GHz
Impedance		50		Ohms
VSWR			2:1	
Insertion Loss			4.75	dB
RF to Bias Isolation	40			dB
DC Voltage			25	Vdc
DC Current			500	mA
Input Power (CW)			1	Watts

Electrical Specification Notes: Values at +25°C, sea level.

Mechanical Specifications

Size	
Length	1.2 in [30.48 mm]
Width	0.63 in [16 mm]
Height	0.5 in [12.7 mm]
Weight	0.0625 lbs [28.35 g]
Package Type	Connectorized
-	

Connectors

RF Connector

Connector
2.92mm Female
Beryllium Copper, Gold
Passivated Stainless Steel



Configuration:

- RF Port Connector: 2.92mm
 Female
- DC/RF Port Connector: 2.92mm Female
- DC Port Connector: Solder Pin

Features:

- 30 kHz to 40 GHz Frequency Range
- Isolation 40 dB Min
- Insertion Loss < 4.75 dB
- 500 mA / 25 VDC Bias

Applications:

- Amplifier Biasing
- DC Return / Block
- Transmitting Power With a Single Coax
- Test and Measurement
- Communication Systems
- Wireless Systems

Fairview Microwave 1130 Junction Dr. #100 Allen, TX 75013 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





RF/DC Connector

Connector		
2.92mm Female		
Beryllium Copper, Gold		
Passivated Stainless Steel		


DC Port

Description	Connector
Туре	Solder Pin

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:



2.92mm Bias Tee From 0.03 MHz to 40 GHz Rated To 500 mA And 25 Volts DC from Fairview Microwave is in-stock and available to ship same-day. All of our RF/microwave products are available off-the-shelf from our ISO 9001:2008 certified facilities in Allen, Texas. Fairview Microwave is RF on-demand.

For additional information on this product, please click the following link: 2.92mm Bias Tee From 0.03 MHz to 40 GHz Rated To 500 mA And 25 Volts DC SB4000A


URL: https://www.fairviewmicrowave.com/2.92mm-bias-tee-0.03-mhz-40-ghz-500-ma-25-volts-dc-sb4000a-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Fairview Microwave reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Fairview Microwave does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Fairview Microwave does not assume any liability arising out of the use of any part or documentation.

1130 Junction Dr. #100 Allen, TX 75013 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689







FAIRVIEW MICROWAVE INC.	NOTES: 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL. 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME. 3. DIMENSIONS ARE IN INCHES [mm].				
TITLE 2.92mm Bias Tee From 0.03 MHz to 40 GHz Rated To 500 mA And 25 Volts DC	DWG NO SB4000A			CAGE CODE 3FKR5	
	CAD FILE 011415	SHEET	SCALE	N/A	SIZE A

1130 Junction Dr. #100 Allen, TX 75013 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689